



Table of Contents

Table of Contents	1	SETUP Audio Settings	36
Usage Notice	2	OPTIONS	37
Safety Information	2	OPTIONS Advanced	38
Precautions	3	OPTIONS Lamp Settings	39
Eye Safety Warnings	5	Appendices	40
Product Features	5	Troubleshooting	40
Introduction	6	Replacing the lamp	45
Package Overview	6	Compatibility Modes	47
Product Overview	7	Computer Compatibility	47
Main Unit	7	Video Compatibility	48
Control Panel	8	3D input Compatibility	49
Input/Output Connections	9	RS232 Commands and Protocol	
Remote Control	10	Function List	50
Installation	11	RS232 Pin Assignments	50
Connecting the Projector	11	RS232 Protocol Function List	51
Connect to Computer/Notebook	11	Ceiling Mount Installation	54
Connect to Video Sources	12	Optoma Global Offices	55
Powering On/Off the Projector	13	Regulation & Safety Notices	57
Powering On the Projector	13		
Powering Off the Projector	14		
Warning Indicator	14		
Adjusting the Projected Image	15		
Adjusting the Projector's Height	15		
Adjusting the Projector's Focus	16		
Adjusting Projection Image Size	16		
User Controls	18		
Control Panel & Remote Control	18		
Control Panel	18		
Remote Control	19		
On-screen Display Menus	21		
How to operate	21		
Menu Tree	22		
IMAGE	24		
IMAGE Advanced	26		
DISPLAY	28		
DISPLAY 3D	30		
SETUP	31		
SETUP Security	33		
SETUP Signal	35		

Safety Information

	The lightning flash with arrow head within an equilateral triangle is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.
	The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

WARNING: TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE. DANGEROUS HIGH VOLTAGES ARE PRESENT INSIDE THE ENCLOSURE. DO NOT OPEN THE CABINET. REFER SERVICING TO QUALIFIED PERSONNEL ONLY.

Class B emissions limits

This Class B digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

Important Safety Instruction

1. Do not block any ventilation openings. To ensure reliable operation of the projector and to protect from over heating, it is recommended to install the projector in a location that does not block ventilation. As an example, do not place the projector on a crowded coffee table, sofa, bed, etc. Do not put the projector in an enclosure such as a book case or a cabinet that restricts air flow.
2. Do not use the projector near water or moisture. To reduce the risk of fire and/or electric shock, do not expose the projector to rain or moisture.
3. Do not install near heat sources such as radiators, heaters, stoves or any other apparatus such as amplifiers that emits heat.
4. Clean only with dry cloth.
5. Only use attachments/accessories specified by the manufacturer.
6. Do not use the unit if it has been physically damaged or abused.
Physical damage/abuse would be (but not limited to):
 - Unit has been dropped.
 - Power supply cord or plug has been damaged.
 - Liquid has been spilled on to the projector.
 - Projector has been exposed to rain or moisture.
 - Something has fallen in the projector or something is loose inside.Do not attempt to service the unit yourself. Opening or removing covers may expose you to dangerous voltages or other hazards. Please call Optoma before you send the unit for repair.
7. Do not let objects or liquids enter the projector. They may touch dangerous voltage points and short out parts that could result in fire or electric shock.
8. See projector enclosure for safety related markings.
9. The unit should only be repaired by appropriate service personnel.

Precautions



Please follow all warnings, precautions and maintenance as recommended in this user's guide.

- ■ Warning- Do not look into the projector's lens when the lamp is on. The bright light may hurt and damage your eyes.
- ■ Warning- To reduce the risk of fire or electric shock, do not expose this projector to rain or moisture.
- ■ Warning- Please do not open or disassemble the projector as this may cause electric shock.
- ■ Warning- When replacing the lamp, please allow the unit to cool down. Follow instructions as described on pages 44-45.
- ■ Warning- This projector will detect the life of the lamp itself. Please be sure to change the lamp when it shows warning messages.
- ■ Warning- Reset the "Lamp Reset" function from the on-screen display "OPTIONS | Lamp Settings" menu after replacing the lamp module (refer to page 38).
- ■ Warning- When switching the projector off, please ensure the cooling cycle has been completed before disconnecting power. Allow 90 seconds for the projector to cool down.
- ■ Warning- Do not use lens cap when projector is in operation.
- ■ Warning- When the lamp is approaching the end of its lifetime, the message "Lamp Warning: Lamp life exceeded." will show on the screen. Please contact your local reseller or service center to change the lamp as soon as possible.
- ■ Warning- Do not look into or point the laser pointer on your remote control into your or someone's eyes. Laser pointer can cause permanent damage to eyesight.

Usage Notice

Do:

- ❖ Turn off and unplug the power plug from the AC outlet before cleaning the product.
- ❖ Use a soft dry cloth with mild detergent to clean the display housing.
- ❖ Disconnect the power plug from AC outlet if the product is not being used for a long period of time.

Do not:

- ❖ Block the slots and openings on the unit provided for ventilation.
- ❖ Use abrasive cleaners, waxes or solvents to clean the unit.
- ❖ Use under the following conditions:
 - In extremely hot, cold or humid environments.
 - ▶ Ensure that the ambient room temperature is within 5 - 35°C.
 - ▶ Relative Humidity is 5 - 35°C, 80% (Max.), non-condensing.
 - In areas susceptible to excessive dust and dirt.
 - Near any appliance generating a strong magnetic field.
 - In direct sunlight.

Eye Safety Warnings



- Avoid staring/facing directly into the projector beam at all times. Keep your back to the beam as much as possible.
- When projector is used in a classroom, adequately supervise students when they are asked to point out something on the screen.
- In order to minimize the lamp power, use room blinds to reduce ambient light levels.


Product Features

- WXGA (1280x800) Native resolution
- HD compatible – 1080p supported
- BrilliantColor™ Technology
- Security Bar and Kensington Lock
- RS232 control
- Rapid shutdown
- Built-in speaker


Introduction

Package Overview


Unpack and inspect the box contents to ensure all parts listed below are in the box. If something is missing, please contact your nearest customer service center.




Projector with lens cap



Power Cord 1.8m




VGA Cable 1.8m



2 × AAA Batteries



IR Remote Control



VGA/RCA Adaptor



❖ Due to different applications in each Country, some regions may have different accessories.


Documentation :

- User's Manual
- Warranty Card
- Quick Start Card
- WEEE Card
(for EMEA only)

Introduction

Product Overview


Main Unit



- | | |
|-------------------------|-------------------------------|
| 1. Control Panel | 6. Security Bar |
| 2. Focus Ring | 7. Input / Output Connections |
| 3. Lens | 8. Power Socket |
| 4. IR Receivers | |
| 5. Tilt-Adjustment Feet | |

Introduction


Control Panel



1. AV Mute
2. Menu
3. Source
4. Enter
5. Re-Sync
6. Power
7. Keystone Correction
8. Four Directional Select Keys
9. On/Standby LED
10. Lamp LED
11. Temp LED
12. IR Receiver

Introduction


Input/Output Connections



1. VGA/YPbPr/ Connector
(PC Analog Signal/Component Video Input/HDTV/YPbPr)
2. HDMI 1 Connector
3. HDMI 2 Connector
4. S-Video Input Connector
5. Composite Video Input Connector
6. Audio Output Connector (3.5mm Mini Jack)
7. 3D Sync Out (5V)
8. Power Socket
9. RS-232 Connector (9-pin)
10. Left RCA Audio Input Connector
11. Right RCA Audio Input Connector
12. Kensington™ Lock Port
13. Security Bar

Introduction


Remote Control



Installation

Connecting the Projector

Connect to Computer/Notebook




- ❖ Due to the difference in applications for each country, some regions may have different accessories.
- ❖ (*) Optional accessory

1.....	Power Cord
2.....	*DVI/HDMI Cable
3.....	VGA Cable
4.....	*RS232 Cable
5.....	*Audio Input Cable
6.....	*Emitter cable

Installation

Connect to Video Sources




- ❖ Due to the difference in applications for each country, some regions may have different accessories.
- ❖ (*) Optional accessory

1.....	Power Cord
2.....	*HDMI Cable
3.....	VGA/RCA Adaptor
4.....	*S-Video Cable
5.....	*Composite Video Cable
6.....	*Audio Cable Jack/RCA
7.....	*Emitter cable


Powering On/Off the Projector

Powering On the Projector

1. Remove the lens cap. ❶
2. Securely connect the power cord and signal cable. When connected, the ON/STANDBY LED will turn Amber.
3. Turn on the lamp by pressing “” button either on the top of the projector or on the remote. The ON/STANDBY LED will now turn Green. ❷

The startup screen will display in approximately 10 seconds. The first time you use the projector, you will be asked to select the preferred language and power saving mode.


4. Turn on and connect the source that you want to display on the screen (computer, notebook, video player, etc). The projector will detect the source automatically. If not, push menu button and go to “OPTIONS”. Make sure that the “Source Lock” has been set to “Off”.
- ❖ If you connect multiple sources at the same time, press the “SOURCE” button on the control panel or direct source keys on the remote control to switch between inputs.







- ❖ Turn on the projector first and then select the signal sources.

Installation


Powering Off the Projector

1. Press the “” button on the remote control or on the control panel to turn off the projector. The following message will be displayed on the screen.



Press the “” button again to confirm otherwise the message will disappear after 15 seconds. When you press the “” button for the second time, the projector will display countdown timer and will shut down.

2. The cooling fans continue to operate for about 10 seconds for cooling cycle and the ON/STANDBY LED will Flash Green. When the ON/STANDBY LED lights solid Amber, the projector has entered standby mode.

If you wish to turn the projector back on, you must wait until the projector has completed the cooling cycle and has entered standby mode. Once in standby mode, simply press “” button to restart the projector.

3. Disconnect the power cord from the electrical outlet and the projector.
4. Do not turn on the projector immediately following a power off procedure.

Warning Indicator

When the warning indicators (see below) come on, the projector will automatically shutdown:



- ❖ Contact the nearest service center if the projector displays these symptoms. See pages 54-55 for more information.
- ❖ “LAMP” LED indicator is lit red and if “On/Standby” indicator flashes amber.
- ❖ “TEMP” LED indicator is lit red and if “On/Standby” indicator flashes amber. This indicates the projector has overheated. Under normal conditions, the projector can be switched back on.
- ❖ “TEMP” LED indicator flashes red and if “On/Standby” indicator flashes amber.


Unplug the power cord from the projector, wait for 30 seconds and try again. If the warning indicator light up again, please contact your nearest service center for assistance.

Adjusting the Projected Image

Adjusting the Projector's Height

The projector is equipped with elevator feet for adjusting the image height.

1. Locate the adjustable foot you wish to modify on the underside of the projector.
2. Rotate the adjustable ring clockwise to raise the projector or counter clockwise to lower it. Repeat with the remaining feet as needed.




Installation

Adjusting the Projector's Focus


To focus the image, rotate the focus ring until the image is clear.

- ▶ WXGA series: The projector will focus at distances from 1.64 to 16.40 feet (0.5 to 5.0 meters).



Adjusting Projection Image Size

- ▶ WXGA series: Projection Image Size from 34.0" to 322.0" (0.8 to 8.2 meters).



Installation


WXGA

Diagonal length (inch) size of 16:10 Screen	Screen Size W x H				Projection Distance (D)		Offset (Hd)	
	(m)		(inch)		(m)	(feet)	(m)	(feet)
	Width	Height	Width	Height	wide	wide		
36.30	0.78	0.49	30.78	19.24	0.56	-	0.06	0.20
44.00	0.95	0.59	37.31	23.32	0.68	2.24	0.07	0.24
60.00	1.29	0.81	50.87	31.80	0.93	3.05	0.10	0.33
70.00	1.51	0.94	59.35	37.10	1.09	3.56	0.12	0.38
80.00	1.72	1.08	67.83	42.40	1.24	4.07	0.13	0.44
90.00	1.94	1.21	76.31	47.69	1.40	4.58	0.15	0.49
100.00	2.15	1.35	84.79	52.99	1.55	5.09	0.17	0.55
120.00	2.58	1.62	101.75	63.59	1.86	6.10	0.20	0.66
150.00	3.23	2.02	127.19	79.49	2.33	7.63	0.25	0.82
180.00	3.88	2.42	152.62	95.39	2.79	9.16	0.30	0.99
250.00	5.38	3.37	211.98	132.49	3.88	12.72	0.42	1.37
302.00	6.50	4.07	256.07	160.04	4.68	15.36	0.50	1.65
362.00	7.80	4.87	306.94	191.84	5.61	18.41	0.60	1.98

❖ This table is for user's reference only.

Control Panel & Remote Control

Control Panel




Using the Control Panel

POWER		Refer to the “Power On/Off the Projector” section on pages 13-14.
RE-SYNC		Automatically synchronize the projector to the input source.
Enter		Confirm your item selection.
SOURCE		Press “SOURCE” to select an input signal.
Menu		Press “Menu” to launch the on-screen display (OSD) menu. To exit OSD, Press “Menu” again.
AV MUTE		Momentarily turns off/on the audio and video.
Four Directional Select Keys		Use to select items or make adjustments to your selection.
Keystone		Use to adjust image distortion caused by tilting the projector. (± 40 degrees)
Lamp LED		Indicate the projector’s lamp status.
Temp LED		Indicate the projector’s temperature status.
ON/STAND-BY LED		Indicate the projector’s status.

User Controls


Remote Control



Using the Remote Control

Power On		Refer to the “Power On” section on page 13.
Power Off		Refer to the “Power On/Off the Projector” section on page 14.
Mode		Select the display mode from Cinema, Bright, Photo, Reference and User.
4:3-I		Scale the image at a 4:3-I (960x720) aspect ratio.
4:3-II		Scale the image at a 4:3-II (1066x800) aspect ratio.
16:9		Scale the image at a 16:9 (1280x720) aspect ratio.
16:10		Scale the image at a 16:10 (1280x800) aspect ratio.
LBX		Enable the viewing of the letterboxed nonan- morphically enhanced movie at full screen width. Part of the original image will be lost if the image aspect ratio is less than 2.35:1.
Native		The input source will be displayed without scaling.
Brightness		Adjust the brightness of the image.
Contrast		Control the degree of difference between the lightest and darkest parts of the picture.
3D Format		For Broadcast 3D signals in “3D format”.
3D		Press the “3D” to turn the 3D OSD menu on/ off.
Vol+ / Vol -		Adjust to increase / decrease the volume.

User Controls



Using the Remote Control


Enter		Confirm your item selection.
Source		Press "Source" to select an input signal.
Re-sync		Automatically synchronizes the projector to the input source.
Menu		Display or exit the on-screen display menus for projector.
HDMI 1		Press "HDMI 1" to choose source from HDMI 1 connector.
HDMI 2		Press "HDMI 2" to choose source from HDMI 2 connector.
VGA		Press "VGA" to choose source from VGA/SCART/YPbPr connector.
S-Video		Press "S-Video" to choose S-Video source.
Video		Press "Video" to choose Composite video source.
Four Directional Select Keys		Use ▲ ▼ ◀ ▶ to select items or make adjustments to your selection.

On-screen Display Menus

The Projector has multilingual On-screen Display menus that allow you to make image adjustments and change a variety of settings. The projector will automatically detect the source.



How to operate

1. To open the OSD menu, press “Menu” on the Remote Control or Projector Keypad.
2. When OSD is displayed, use ◀▶ keys to select any item in the main menu. While making a selection on a particular page, press ▼ or “Enter” key to enter sub menu.
3. Use ▲▼ keys to select the desired item and adjust the settings using ◀▶ key.
4. Select the next item to be adjusted in the sub menu and adjust as described above.
5. Press “Enter” to confirm, and the screen will return to the main menu.
6. To exit, press “MENU” again. The OSD menu will close and the projector will automatically save the new settings.



User Controls

Menu Tree

Main Menu	Sub Menu	Settings	
Image	Display Mode	Cinema / Bright / Presentation / Game / Blackboard / Classroom / 3D / User	
	Brightness	-50 ~ +50	
	Contrast	-50 ~ +50	
	Sharpness	1~15	
	#1 Color	-50 ~ +50	
	#1 Tint	-50 ~ +50	
	Advanced	Gamma	Film / Video / Graphics / Standard
		BrilliantColor™	0~10
		Color Temp.	Warm / Medium / Cold
		Color	Red Gain / Green Gain / Blue Gain / Red Bias / Green Bias / Blue Bias / Cyan / Magenta / Yellow / Reset / Exit
		Color Space	AUTO / RGB / YUV #2 AUTO / RGB (0-255) / RGB (16-235) / YUV
		Input Source	VGA / S-Video / Video / HDMI 1 / HDMI 2
		Exit	
Display	Format	4:3-I / 4:3-II / 16:9 / 16:10 / LBX / Native / AUTO	
	Edge Mask	0~10	
	Zoom	-5 ~ +25	
	V Image Shift	-50 ~ +50	
	V Keystone	-40 ~ +40	
	3D	3D Mode	DLP-Link / VESA 3D
		3D -> 2D	3D / L / R
		3D Format	Auto / SBS / Top and Bottom / Frame Sequential
		#3 3D Sync. Invert	On / Off
		Exit	
Setup	Language	English / Deutsch / Français / Italiano / Español / Português / Svenska / Nederlands / Norsk/Dansk / Polski / Suomi / Русский / ελληνικά / Magyar / Čeština / العربية / فارسی / 繁體中文 / 简体中文 / 日本語 / 한국어 / ไทย / Türkçe	
	Projection		
	Menu Location		
	#4 Signal	Automatic	Enable / Disable
		Frequency (VGA)	-5~5
		Phase (VGA)	0~63
		H. Position (VGA)	-5~5
		V. Position (VGA)	-5~5
		Exit	


User Controls

Main Menu	Sub Menu	Settings		
Setup	Security	Security	On / Off	
		Security Timer	Month / Day / Hour	
		Change Password		
		Exit		
	Projector ID		0~99	
	Audio Settings	Internal Speaker	On / Off	
		Mute	On / Off	
		Volume	0~10	
		Audio Input	Default / Audio / HDMI	
		Exit		
Options	Source Lock		On / Off	
	High Altitude		On / Off	
	Information Hide		On / Off	
	Keypad Lock		On / Off	
	Background Color		Black / Red / Blue / Green / White	
	Test Pattern		None / Grid / White Pattern	
	Advanced	Direct Power On		On / Off
		Auto Power Off (min.)		0~180
		Sleep Timer (min.)		0~995
		Exit		
	Lamp Settings	Lamp Hours		
		Lamp Reminder		On / Off
		Brightness Mode		STD / Bright
Lamp Reset			Yes / No	
Exit				
Reset			Yes / No	



- ❖ Please note that the on-screen display (OSD) menus vary according to the signal type selected and the projector model you are using.
- ❖ (#1) "Color" and "Tint" are only supported in Video mode.
- ❖ (#2) For HDMI source only.
- ❖ (#3) "3D Sync Invert" is only available when 3D is enabled.
- ❖ (#4) "Signal" is only supported in Analog VGA (RGB) signal.

IMAGE



Display Mode

There are many factory presets optimized for various types of images.

- ▶ Presentation: Good color and brightness from PC input.
- ▶ Bright: Maximum brightness from PC input.
- ▶ Cinema: For home theater.
- ▶ Game: For game mode.
- ▶ Blackboard: This mode should be selected to achieve optimum color settings when projecting onto a blackboard (green).
- ▶ Classroom: This mode is recommended for projecting in a classroom.
- ▶ User: User's settings.
- ▶ 3D: Recommended setting for 3D mode enabled. Any further adjustments by the user in 3D will be saved in this mode for further use.

Contrast

The contrast controls the degree of difference between the lightest and darkest parts of the picture.

- ▶ Press the ◀ to decrease the contrast.
- ▶ Press the ▶ to increase the contrast.

Brightness

Adjust the brightness of the image.

- ▶ Press the ◀ to darken image.
- ▶ Press the ▶ to lighten the image.



NOTE

❖ “Color” and “Tint” functions are only supported under Video mode.

Color

Adjust a video image from black and white to fully saturated color.

- ▶ Press the ◀ to decrease the amount of saturation in the image.
- ▶ Press the ▶ to increase the amount of saturation in the image.

Tint

Adjust the color balance of red and green.


- ▶ Press the ◀ to increase the amount of green in the image.
- ▶ Press the ▶ to increase the amount of red in the image.

Sharpness

Adjust the sharpness of the image.

- ▶ Press the ◀ to decrease the sharpness.
- ▶ Press the ▶ to increase the sharpness.

IMAGE | Advanced



BrilliantColor™

This adjustable item utilizes a new color-processing algorithm and system level enhancements to enable higher brightness while providing true, more vibrant colors in picture. The range is from “0” to “10”. If you prefer a stronger enhanced image, adjust toward the maximum setting. For a smoother, more natural image, adjust toward the minimum setting.

Gamma

This allows you to set up gamma curve type. After the initial setup and fine tuning is completed, utilize the Gamma Adjustment steps to optimize your image output.




- ▶ Film: for home theater.
- ▶ Video: for video or TV source.
- ▶ Graphics: for image source.
- ▶ Standard: for standardized setting.



Color Temp


If set to cold temperature, the image looks more blue. (cold image)
If set to warm temperature, the image looks more red.
(warm image)

User Controls

Color Settings

Press  into the next menu as below and then use  or  to select item.

- ▶ Red/Green/Blue/Cyan/Magenta/Yellow: Use  or  to select Red, Green, Blue, Cyan, Magenta and Yellow Colors.
- ▶ Reset: Choose “Yes” to return the factory default settings for color adjustments.





❖ (*) For HDMI only.

Color Space


Select an appropriate color matrix type from AUTO, RGB, RGB(0-255)^(*), RGB(16-235)^(*) or YUV.

Input Source

Use this option to enable / disable input sources. Press  to enter the sub menu and select which sources you require. Press “Enter” to finalize the selection. The projector will not search for inputs that are not selected.



DISPLAY



Format

Use this function to choose your desired aspect ratio.

- ▶ 4:3-I: This format is for 4×3-I input sources.
- ▶ 4:3-II: This format is for 4×3-II input sources.
- ▶ 16:9: This format is for 16×9 input sources, like HDTV and DVD enhanced for Wide screen TV.
- ▶ 16:10: This format is for 16×10 input sources, like widescreen laptops.
- ▶ LBX: This format is for non-16x9, letterbox source and for users who use external 16x9 lens to display 2.35:1 aspect ratio using full resolution.
- ▶ Native: This format displays the original image without any scaling.
- ▶ AUTO: Automatically selects the appropriate display format.

Aspect ratio (source detected)	Resize image WXGA model
4:3-I	960 x 720 center
4:3-II	1066 x 800 center
16:9	1280 x 720 center
16:10	1280 x 800 center
LBX	1280 x 960 center, then get the central 1280 x 800 image to display
Native	Resize image of native change to above description not pixels resolution.



- ❖ Each I/O has different setting of “Edge Mask”.
- ❖ “Edge Mask” and “Zoom” can’t work at same time.

Detail informations about LBX mode:

1. Some Letter-Box DVDs are not enhanced for 16x9 TVs. In this situation, the image will not look right when displayed in 16:9 mode.

In this situation, please try to using the 4:3 mode to view the DVD.

If the content is not 4:3, there will be black bars around the image in 16:9 display. For this type of content, you can use LBX mode to fill the image on the 16:9 display.

2. If you use an external anamorphic lens, this LBX mode also allows you to watch a 2.35:1 content (include Anamorphic DVD and HDTV film source) that support anamorphic wide is enhanced for 16x9 Display in a wide 2.35:1 image.

In this case, there are no black bars. Lamp power and vertical resolution are fully utilized.

Zoom

- ▶ Press the ◀ to reduce the size of an image.
- ▶ Press the ▶ to magnify an image on the projection screen.

Edge Mask

Edge mask function removes the noise in a video image. Edge mask the image to remove video encoding noise on the edge of video source.

V Image Shift

Shift the projected image position vertically.

V Keystone

Press the ◀ or ▶ to adjust image distortion vertically. If the image looks trapezoidal, this option can help make the image rectangular.

DISPLAY | 3D



- ❖ “3D sync. Invert” function wouldn’t save the setting. It will set to “Off” when powers on and changes source.
- ❖ 3D Format is only supported on 3D Timing on page 49.

3D Mode

- ▶ DLP Link: Select “DLP Link” to use optimized settings for DLP Link 3D images. (For DLP glasses, please refer to page 15).
- ▶ VESA 3D: Select “VESA 3D” to use optimized setting for VESA 3D images. (For 3D emitter, please refer to page 13).

3D -> 2D

- ▶ 3D: Display left and right frames of 3D content.
- ▶ L (Left): Display the left frame of 3D content.
- ▶ R (Right): Display the right frame of 3D content.


3D Format

- ▶ Auto : When a 3D identification signal is detected, the 3D format is selected automatically.
- ▶ SBS: Display 3D signal in “Side-by-Side” format.
- ▶ Top and Bottom: Display 3D signal in “Top and Bottom” format.
- ▶ Frame Sequential: Display 3D signal in “Frame Sequential” format.

3D Sync. Invert

- ▶ Press the “On” to invert left and right frame contents.
- ▶ Press the “Off” for default frame contents.

SETUP



Language

Choose the multilingual OSD menu. Press ◀ or ▶ into the sub menu and then use the ▲ or ▼ key to select your preferred language. Press “Enter” to finalize the selection.




- ❖ Rear-Desktop and Rear-Ceiling are to be used with a translucent screen.




Projection

- ▶  Front-Desktop

This is the default selection. The image is projected straight on the screen.


- ▶  Rear-Desktop

When selected, the image will appear reversed.

- ▶  Front-Ceiling

When selected, the image will turn upside down.

User Controls

- ▶  Rear-Ceiling

When selected, the image will appear reversed in upside down position.


Menu Location

Choose the menu location on the display screen.

Projector ID

ID definition can be set up by menu (range 0~99), and allow user control an individual projector by RS232. Refer to pages 50~53 for the complete list of RS232 commands.

SETUP | Security



Security

- ▶ On: Choose “On” to use security verification when the turning on the projector.
- ▶ Off: Choose “Off” to be able to switch on the projector without password verification.




- ❖ Pass-code default value is “1234” (first time).

Security Timer

Can be select the time (Month/Day/Hour) function to set the number of hours the projector can be used. Once this time has elapsed you will be requested to enter your password again.

Change Password


- ▶ First time:
 1. Press “←” to set the password.
 2. The password has to be 4 digits.
 3. Use number button on the remote to enter your new password and then press “←” key to confirm your password.
- ▶ Change Password:
 1. Press “←” to input old password.
 2. Use number button to enter current password and then press “←” to confirm.
 3. Enter new password (4 digits in length) using the number buttons on the remote, then press “←” to confirm.
 4. Enter new password again and press “←” to confirm.



User Controls

- ▶ If the incorrect password is entered 3 times, the projector will automatically shut down.
- ▶ If you have forgotten your password, please contact your local office for support.

SETUP | Signal



- ❖ “Signal” is only supported in Analog VGA (RGB) signal.

Automatic

Automatically selects the signal. If you use this function, the Phase, frequency items are grayed out, and if Signal is not automatic, the phase, frequency items will appear for user to manually tune and saved in settings after that for next time projector turns off and on again.

Phase

Synchronize the signal timing of the display with the graphic card. If the image appears to be unstable or flickers, use this function to correct it.

Frequency

Change the display data frequency to match the frequency of your computer's graphic card. Use this function only if the image appears to flicker vertically.


H. Position

- ▶ Press the ◀ to move the image left.
- ▶ Press the ▶ to move the image right.

V. Position

- ▶ Press the ◀ to move the image down.
- ▶ Press the ▶ to move the image up.

SETUP | Audio Settings



Internal Speaker

Choose the “On” or “Off” to turn on or off the internal speaker.

Mute

- ▶ Choose the “On” to turn mute on.
- ▶ Choose the “Off” to turn mute off.

Volume


- ▶ Press the ◀ to decrease the volume.
- ▶ Press the ▶ to increase the volume.

Audio Input

The default audio settings are on the back panel of the projector. Use this option to reassign any of the Audio Inputs to the current image source.

- ▶ AUDIO: Audio connector port.
- ▶ HDMI: HDMI connector port.

OPTIONS



Source Lock

- ▶ On: The projector will only search current input connection.
- ▶ Off: The projector will search for other signals if the current input signal is lost.

High Altitude

When “On” is selected, the fans will spin faster. This feature is useful in high altitude areas where the air is thin.

Information Hide

- ▶ On: Choose “On” to hide the info message.
- ▶ Off: Choose “Off” to show the “searching” message.

Keypad Lock

When the keypad lock function is “On”, the control panel will be locked however, the projector can be operated by the remote control. By selecting “Off”, you will be able to reuse the control panel.

Background Color

Use this feature to display a “Black”, “Red”, “Blue”, “Green” or “White”, screen when no signal is available.

Test Pattern

Display a test pattern. There are Grid, White pattern and None.

Reset

Choose “Yes” to return the display parameters on all menus to the factory default settings.



- ❖ To turn off the keypad lock, press and hold “Enter” key on top of the projector for 5 seconds.

OPTIONS | Advanced



Direct Power On

Choose “On” to activate Direct Power mode. The projector will automatically power on when AC power is supplied, without pressing the “**⏻**” key on the projector control panel or on the remote control.


Auto Power Off (min)

Sets the countdown timer interval. The countdown timer will start, when there is no signal being sent to the projector. The projector will automatically power off when the countdown has finished (in minutes).

Sleep Timer (min)

Sets the countdown timer interval. The countdown timer will start, with or without a signal being sent to the projector. The projector will automatically power off when the countdown has finished (in minutes).

OPTIONS | Lamp Settings



Lamp Hours

Display the projection time.

Lamp Reminder

Choose this function to show or to hide the warning message when the changing lamp message is displayed.

The message will appear 30 hours before suggested replacement of lamp.

Brightness Mode

- ▶ STD: Choose “STD” to dim the projector lamp which will lower power consumption and extend the lamp life.
- ▶ BRIGHT: Choose “BRIGHT” to increase the brightness.
- ▶ Image AI: Image AI improves the contrast of the picture by optimizing the brightness of the lamp according to the picture content. Image AI helps to ensure that details in dark scenes are visible, whilst maintaining bright and vivid images.

Lamp Reset

Reset the lamp hour counter after replacing the lamp.

Troubleshooting

If you experience a problem with your projector, please refer to the following information. If a problem persists, please contact your local reseller or service center.

? No image appears on-screen

- ▶ Ensure all the cables and power connections are correctly and securely connected as described in the “Installation” section.
- ▶ Ensure all the pins of connectors are not bent or broken.
- ▶ Check if the projection lamp has been securely installed. Please refer to the “Replacing the lamp” section.
- ▶ Make sure you have removed the lens cap and the projector is switched on.
- ▶ Ensure that the “AV mute” feature is not turned on.

? Partial, scrolling or incorrectly displayed image

- ▶ Press “Re-SYNC” on the remote.
- ▶ If you are using a PC:

For Windows 95, 98, 2000, XP, Windows 7:

1. Open the “My Computer” icon, the “Control Panel” folder, and then double click on the “Display” icon.
2. Select the “Settings” tab.
3. Verify that your display resolution setting is lower than or equal to UXGA (1600 × 1200).
4. Click on the “Advanced Properties” button.

If the projector is still not projecting the whole image, you will also need to change the monitor display you are using. Refer to the following steps.

5. Verify the resolution setting is lower than or equal to UXGA (1600 × 1200).
6. Select the “Change” button under the “Monitor” tab.

Appendices

7. Click on “Show all devices”. Next, select “Standard monitor types” under the SP box; choose the resolution mode you need under the “Models” box.
 8. Verify that the resolution setting of the monitor display is lower than or equal to UXGA (1600 × 1200).
- ▶ If you are using a Notebook:
1. First, follow the steps above to adjust resolution of the computer.
 2. Press the appropriate keys listed below for your notebook manufacturer to send signal out from notebook to projector.
Example: [Fn]+[F4]

Acer ⇨	[Fn]+[F5]	IBM/Lenovo ⇨	[Fn]+[F7]
Asus ⇨	[Fn]+[F8]	HP/Compaq ⇨	[Fn]+[F4]
Dell ⇨	[Fn]+[F8]	NEC ⇨	[Fn]+[F3]
Gateway ⇨	[Fn]+[F4]	Toshiba ⇨	[Fn]+[F5]

Mac Apple:

System Preference ⇨ Display ⇨ Arrangement ⇨ Mirror display

- ▶ If you experience difficulty changing resolutions or your monitor freezes, restart all equipment including the projector.

[?] The screen of the Notebook or PowerBook computer is not displaying your presentation

- ▶ If you are using a Notebook PC

Some Notebook PCs may deactivate their own screens when a second display device is in use. Each has a different way to be reactivated. Refer to your computer’s manual for detailed information.

[?] Image is unstable or flickering

- ▶ Use “Phase” to correct it. See page 35 for more information.
▶ Change the monitor color setting on your computer.

[?] Image has vertical flickering bar

- ▶ Use “Frequency” to make an adjustment. See page 35 for more information.
▶ Check and reconfigure the display mode of your graphic card to make it compatible with the projector.

[?] Image is out of focus

- ▶ Make sure the lens cap is removed.
- ▶ Adjust the Focus Ring on the projector lens.
- ▶ Make sure the projection screen is between the required distance. See page 16.

[?] The image is stretched when displaying 16:9 DVD title

- ▶ When you play anamorphic DVD or 16:9 DVD, the projector will show the best image when the projector display mode is set to 16:9 in the OSD.
- ▶ If you play 4:3 format DVD titles, please change the format to 4:3 in the projector OSD.
- ▶ If the image is still stretched, you will also need to adjust the aspect ratio by referring to the following:
- ▶ Please setup the display format as 16:9 (wide) aspect ratio type on your DVD player.



[?] Image is too small or too large

- ▶ Move the projector closer to or further from the screen.
- ▶ Press “Menu” button on the remote control or projector panel, go to “DISPLAY → Format” and try the different settings.



❖ Use of Keystone is not recommended.

[?] Image has slanted sides

- ▶ If possible, reposition the projector so that it is horizontally centered on the screen and below the bottom of the screen.
- ▶ Press “ / ” on the projector panel, until the sides are vertical.

[?] Image is reversed

- ▶ Select “SETUP → Projection” from the OSD and adjust the projection direction.




















[?] The projector stops responding to all controls

- ▶ If possible, turn off the projector, then unplug the power cord and wait at least 60 seconds before reconnecting power.
- ▶ Check that “Keypad Lock” is not activated by trying to control the projector with the remote control.



[?] Lamp burns out or makes a popping sound

- ▶ When the lamp reaches its end of life, it will burn out and may make a loud popping sound. If this happens, the projector will not turn on until the lamp module has been replaced. To replace the lamp, follow the procedures in the “Replacing the Lamp” section on pages 44-45.

[?] LED lighting message

Message	  ON/STANDBY LED	  Temp-LED	  Lamp-LED
	(Green/Amber)	(Red)	(Red)
Standby State (Input power cord)	Amber		
Power on (Warming)	Flashing Green		
Lamp lighting	Green		
Power off (Cooling)	Flashing Green		
Error (Over Temp.)	Flashing Amber		
Error (Fan fail)	Flashing Amber	Flashing	
Error (Lamp fail)	Flashing Amber		




Steady light ⇒ 
 No light ⇒ 

* ON/STANDBY LED be ON when OSD appears, be OFF when OSD disappears.

? On Screen Messages


▶ Temperature warning:



▶ Fan failed:



▶ Lamp warning:



▶ Out of display range:




? If the remote control does not work


- ▶ Check the operating angle of the remote control is within $\pm 15^\circ$ both horizontally and vertically of one of the IR receivers on the projector.
- ▶ Make sure there are not any obstructions between the remote control and the projector. Move to within 7 m ($\pm 0^\circ$) of the projector.
- ▶ Make sure the batteries are inserted correctly.
- ▶ Replace batteries if they are exhausted.




Replacing the lamp

The projector automatically detects the lamp life. When the lamp life is nearing the end of use, you will receive a warning message.



When you see this message, please contact your local reseller or service center to change the lamp as soon as possible. Make sure the projector has been cooled down for at least 30 minutes before changing the lamp.




-  Warning: If ceiling mounted, please use caution when opening the lamp access panel. It is recommended to wear safety glasses if changing the bulb when ceiling mounted. "Caution must be used to prevent any loose parts from falling out of projector."
-  Warning: Lamp compartment may be hot! Allow it to cool down before changing the lamp!
-  Warning: To reduce the risk of personal injury, do not drop the lamp module or touch the lamp bulb. The bulb may shatter and cause injury if it is dropped.


Appendices

NOTE

- ❖ The screws on the lamp cover and the lamp cannot be removed.
- ❖ The projector cannot be turned on if the lamp cover has not been placed back on the projector.
- ❖ Do not touch the glass area of the lamp. Hand oil can cause the lamp to shatter. Use a dry cloth to clean the lamp module if it was accidentally touched.



Lamp Replacement Procedure:

1. Switch off the power to the projector by pressing the “” button.
 2. Allow the projector to cool down for at least 30 minutes.
 3. Disconnect the power cord.
 4. Unscrew the two screws on the cover. **1**
 5. Lift up and remove the cover. **2**
 6. Unscrew the two screws on the lamp module. **3**
 7. Lift up the lamp handle and remove the lamp module slowly and carefully. **4**
- To replace the lamp module, reverse the previous steps.
8. Turn on the projector and use “Lamp Reset” after the lamp module is replaced.

Lamp Reset: (i) Press “Menu” → (ii) Select “OPTIONS” → (iii) Select “Lamp Settings” → (iv) Select “Lamp Reset” → (v) Select “Yes”.

Compatibility Modes

► Computer Compatibility

Mode	Resolution	V-Sync (Hz)		H-Sync (KHz)	
		Anglog	Digital	Anglog	Digital
VGA	640 × 350	70	70	31.50	31.50
VGA	640 × 350	85	85	37.90	37.90
VGA	640 × 400	85	85	37.90	37.90
VGA	640 × 480	60	60	31.50	31.50
VGA	640 × 480	67	67	-	-
VGA	640 × 480	72	72	37.90	37.90
VGA	640 × 480	75	75	37.50	37.50
VGA	720 × 400	70	70	31.50	31.50
VGA	720 × 400	85	85	37.90	37.90
SVGA	800 × 600	56	56	35.20	35.20
SVGA	800 × 600	60	60	37.90	37.90
SVGA	800 × 600	72	72	48.10	48.10
SVGA	800 × 600	75	75	46.90	46.90
SVGA	800 × 600	120	120	-	-
XGA	1024 × 768	60	60	48.40	48.40
XGA	1024 × 768	70	70	56.50	56.50
XGA	1024 × 768	75	75	60.00	60.00
XGA	1024 × 768	120	120	-	-
WXGA	1280 × 800	60	60	49.68	49.64
SXGA	1280 × 1024	60	60	63.98	63.98
	1366 × 768	60	60	-	-
	1440 × 900	60	60	55.94	55.94
	1680 × 1050	60	60	-	-
SXGA+	1400 × 1050	60	60	63.98	63.98
UXGA	1600 × 1200	60	60	75.00	75.00
WSXGA+	1680 × 1050	60	60	65.00	65.00
HD	1280 × 720	60	60	45.00	45.00
HD	1280 × 720	120	120	-	-
HD	1920 × 1080	60	60	-	-



- ❖ For widescreen resolution (WXGA), the compatibility support is dependent on Notebook/PC models.
- ❖ 120Hz input signals may be dependent on graphics cards support.

Appendices

▶ Computer Compatibility

Mode	Resolution	V-Sync (Hz)	H-Sync (KHz)
MAC LC 13"	640 × 480	66.66	34.98
MAC II 13"	640 × 480	66.68	35.00
MAC 16"	832 × 624	74.55	49.73
MAC 19"	1024 × 768	75	60.24
MAC	1152 × 870	75.06	68.68
MAC G4	640 × 480	60	31.35
i MAC DV	1024 × 768	75	60.00
i MAC DV	1152 × 870	75	68.49

▶ Video Compatibility

NTSC	M (3.58MHz), 4.43 MHz
PAL	B, D, G, H, I, M, N
SECAM	B, D, G, K, K1, L
SDTV/HDTV	480i/p, 576i/p, 720p@50Hz/60Hz, 1080i/p@50Hz/60Hz

Appendices

► 3D input Compatibility

HDMI 1.4a 3D timing										
Formats	Modes	Resolution	V.Frequency	H.Frequency	Pixel Rate	DLP link	VESA 3D	Auto 3D format	Auto detection of L/R frame	3D to 2D
			[Hz]	[KHz]	[MHz]					
Frame Packing	720p	1280x720	50	75	148.5	○	○	○	○	○
	720p	1280x720	60	90	148.5	○	○	○	○	○
	1080p	1920x1080	24	54	148.5	○	○	○	○	○
Top and Bottom	720p	1280x720	50	37.5	74.25	○	○	○	○	○
	720p	1280x720	60	45	74.25	○	○	○	○	○
	1080p	1920x1080	24	27	74.25	○	○	○	○	○
Side by Side (half)	1080i	1920x1080	50(25)	33.75	74.25	○	○	○	○	○
	1080i	1920x1080	60(30)	33.75	74.25	○	○	○	○	○


HDMI 1.3 3D timing										
Formats	Modes	Resolution	V.Frequency	H.Frequency	Pixel Rate	DLP link	VESA 3D	Auto 3D format	Auto detection of L/R frame	3D to 2D
			[Hz]	[KHz]	[MHz]					
Frame Sequential	SVGA	800x600	120	76.3	73.25	○	○	x	x	○
	XGA	1024x768	120	97.6	115.5	○	○	x	x	○
	720p	1280x720	120/60			○	○	x	x	○
Side by Side (half)	1080i	1920x1080	50(25)	33.75	74.25	○	○	x	x	○
	1080i	1920x1080	60(30)	33.75	74.25	○	○	x	x	○
Top & Bottom (half)	1080i	1920x1080	50(25)	33.75	74.25	○	○	x	x	○
	1080i	1920x1080	60(30)	33.75	74.25	○	○	x	x	○

VGA 1.3 3D timing										
Formats	Modes	Resolution	V.Frequency	H.Frequency	Pixel Rate	DLP link	VESA 3D	Auto 3D format	Auto detection of L/R frame	3D to 2D
			[Hz]	[KHz]	[MHz]					
Frame Sequential	SVGA	800x600	120	76.3	73.25	○	○	x	x	x
	XGA	1024x768	120	97.6	115.5	○	○	x	x	x
	720p	1280x720	120/60			○	○	x	x	x

CVBS/S-Video										
Formats	Modes	Resolution	V.Frequency	H.Frequency	Pixel Rate	DLP link	VESA 3D	Auto 3D format	Auto detection of L/R frame	3D to 2D
			[Hz]	[KHz]	[MHz]					
Frame Sequential	NTSC	720x480	60	15.73		○	○	x	x	x
	PAL	720x576	50	15.63		○	○	x	x	x

RS232 Commands and Protocol Function List

RS232 Pin Assignments



Pin no.	Spec. (from projector side)
1	N/A
2	RXD
3	TXD
4	N/A
5	GND
6	N/A
7	N/A
8	N/A
9	N/A

Appendices

RS232 Protocol Function List

Optoma Data and HT Projectors

G1750

Baud Rate 9600
 Data Bits 8
 Parity None
 Stop Bits 1
 Flow Control None
 UART16550 FIFO Disable

~	X	X	X	X	X	space	n	CR		
Lead Code	Projector ID	Command ID	Command ID	space	variable	carriage return				
		Function			ASCII	Pass	Fail			
Power		On/Off		n=1/n=0 & 2	~XX00 n	P	F			
Power On with Password					~XX00 1 ~nnnn	P	F			
Re-pin					~XX01 n	P	F			
AV Mute		On/Off		n=1/n=0 & 2	~XX02 n	P	F			
Mute		On/Off		n=1/n=0 & 2	~XX03 n	P	F			
Freeze				n=1	~XX04 n	P	F			
Unfreeze				n=0 & 2	~XX05 n	P	F			
Zoom Plus				n=1	~XX06 n	P	F			
Zoom Minus				n=1	~XX12 n	P	F			
Direct Source Commands		HDMI 1		n=1						
		HDMI 2		n=15						
		VGA 1		n=5						
		VGA 1 SCART		n=7						
		VGA 1 Component		n=8						
		S-Video		n=9						
		Video		n=10						
		Presentation		n=11	~XX20 n	P	F			
		Cinema		n=2						
		Bright		n=5						
User		n=7								
Blackboard		n=8								
Classroom		n=9								
3D		n=12								
Game		n=12								
Brightness		Contrast		n= 50 +50	~XX21 n	P	F			
		Sharpness		n= 50 +50	~XX22 n	P	F			
		Tint		n= 1 +15	~XX23 n	P	F			
		Color		n= 50 +50	~XX44 n	P	F			
		Color Settings	RGB Gain/Bias	Red Gain		n= 50 +50	~XX45 n	P	F	
				Green Gain		n= 50 +50	~XX25 n			
				Blue Gain		n= 50 +50	~XX26 n			
				Red Bias		n= 50 +50	~XX27 n			
				Green Bias		n= 50 +50	~XX28 n			
				Blue Bias		n= 50 +50	~XX29 n			
Open Gain				n= 50 +50	~XX30 n					
Yellow Gain				n= 50 +50	~XX31 n					
Magenta Gain				n= 50 +50	~XX32 n					
Reset				n=1	~XX33 n					
BrilliantColor™		Film		n= 0 - 10	~XX34 n	P	F			
		Video		n=1	~XX35 n	P	F			
		Graphics		n=2	~XX35 n					
		PCStandard		n=3	~XX35 n					
		Warm		n=4	~XX35 n					
		Medium		n=1	~XX36 n	P	F			
		Cold		n=2						
		Auto		n=3						
		RGB 1 (RGB (0-255)*)		n=1	~XX37 n	P	F			
		RGB16 - 235†		n=2						
Advanced		YUV		n=3	~XX39 n	P	F			
		HDMI 1		n=1						
		HDMI 2		n=7	~XX39 n	P	F			
		VGA 1		n=5						
		S-Video		n=8						
		Video		n=10						
		Input Source Filters		4:3		n=1	~XX60 n	P	F	
				16:9		n=2				
				16:10		n=3				
				LDB		n=5				
Native				n=5						
AUTO				n=7						
4:3-II				n=10						
Edge masking				n = 0 - 10	~XX61 n	P	F			
Zoom				n=0-10	~XX62 n	P	F			
H Image Shift				n= 50 +50	~XX63 n	P	F			
V Image Shift		n= 50 +50	~XX64 n	P	F					
V Keystone		n= 50 +50	~XX66 n	P	F					
DISPLAY		Format	3D Mode	DLP Link/YESA 3D		n=1/n=3	~XX20 n	P	F	
				3D->2D	3D / L / R	2D->2D; 3D->3D / 3D->L / 3D->R	n=0/n=1/n=2	~XX40 n	P	F
				3D Settings	3D Format	SBS/Top and Bottom/Frame Sequential/ Auto	Decoding HDMI 1.3 3D timing	n=1/n=3/n=4/n=5	~XX405 n	
				3D Sync. Invert	On/Off	n=0/n=1	~XX31 n			
				English		n=1	~XX70 n	P	F	
		SETUP	Language	German		n=2				
				French		n=3				
				Italian		n=4				
				Spanish		n=5				
				Portuguese		n=6				
Polish				n=7						
Dutch				n=8						
Swedish				n=9						
Norwegian/Danish				n=10						
Finnish				n=11						
Greek		n=12								
Traditional Chinese		n=13								
Simplified Chinese		n=14								
Japanese		n=15								
Korean		n=16								
Russian		n=17								
Hungarian		n=18								
Czech		n=18								

Appendices

Lead Code	X	Projector ID	X	Command ID	X	X	n	CR		
						space	variable	carriage return		
SETUP	Language	Arabic					m20			
		Thai					m21			
		Turkish					m22			
	Projection	Farsi					m23			
		Front-Desktop					m1	-XXT1 n	P	F
		Rear-Desktop					m2			
	Menu Location	Front-Ceiling					m3			
		Rear-Ceiling					m4			
		Top Left					m1	-XXT2 n	P	F
	Signal	Top Right					m2			
		Centre					m3			
		Bottom Left					m4			
	Security	Bottom Right					m5			
		Automatic	Enable/Disable				m1=m0	-XX91 n		
		Frequency					m=-S-+S	-XXT3 n	P	F
		Phase					m=0-SS	-XXT4 n	P	F
		H. Position					m=-S-+S	-XXT5 n	P	F
		V. Position					m=-S-+S	-XXT6 n	P	F
		Security Timer	Month/Day/Hour				m=mm	-XXT7 n	P	F
		Change Password							send back the password to confirm	
		Projector ID	Security	On/Off			m=1m0 & 2	-XXT8 n	P	F
		Internal Speaker		On/Off			m=1m0 & 2	-XX310 n	P	F
	Mute		On/Off			m=1m0 & 2	-XX80 n	P	F	
	Volume					m=0-10	-XX81 n	P	F	
	Audio Input		Default/Audio/HDMI				m=1m2+m6	-XX89 n	P	F
	Source Lock		On/Off			m=1m0 & 2	-XX100 n	P	F	
	High Altitude		On/Off			m=1m0 & 2	-XX101 n	P	F	
	Information Hide		On/Off			m=1m0 & 2	-XX102 n	P	F	
	Keypad Lock		On/Off			m=1m0 & 2	-XX103 n	P	F	
	Keef Pattern		None / Grid / White Pattern			m=0m1m2	-XX105 n	P	F	
Background Color	Blue					m1	-XX104 n	P	F	
	Black					m2				
	Red					m3				
	Green					m4				
	White					m5				
OPTIONS	Direct Power On		On/Off			m=1m0 & 2	-XX105 n	P	F	
	Auto Power Off (min)					n=0-180	-XX106 n	P	F	
	Advanced	Sleep Timer (min)					n=000-995	-XX107 n	P	F
		Lamp Hour					m1	-XX108 n	mm	F
		Lamp Reminder		On/Off			m=1m0 & 2	-XX109 n	P	F
		Brightness Mode		Bright/STD			m1m2	-XX110 n	P	F
		Lamp Reset		Yes			m1	-XX111 n	P	F
	Reset			No			m2			
				Yes			m1	-XX112 n	P	F
				No			m2			
Information from Projector Automatically										
when:	Standby Mode					a=0		INF/Oa		
	Warning up					a=1		INF/Oa		
	Cooling Down					a=2		INF/Oa		
	Out of Range					a=3		INF/Oa		
	Lamp Fail					a=4		INF/Oa		
	Thermal Switch Error					a=5				
	Fan Lock					a=6				
	Over Temperature					a=7				
	Lamp Hours Running Out					a=8				
READ/Return information from projector										
	Information					m1	-XX150 n	Oxabbccddd		
	a = Power State		Off/On			a=0/1				
	b = Lamp Hour					b5bb				
	c = Input Source Commands		None			c00				
			VGA1			c02				
			S-Video			c04				
			Video			c05				
			HDMI1			c07				
			HDMI2			c08				
	d = Firmware Version					d00				
	e = Display mode		None			e00				
			Presentation			e=1				
			Bright			e=2				
			Gamma			e=11				
			User(1)			e=5				
			ISF Day / Backboard			e=7				
			ISF Night / Classroom			e=8				
			Game			e=12				
			3D			e=9				
	Model Name		Depends			G1750 a#21	n = 1	-XX151 n	Oka	
						a=0/1/2				
	Input Source Commands		None/DVI/VGA-1/VGA-2/S-Video/Video/BNC/HDMI1/HDMI2/HDMI3/Wireless/Component			m1	-XX121 n	Oka	a=0/1/2/3/4/5/6/7/8/9/10/11	
	Software Version					m1	-XX122 n	Ox0000		
	Display Mode		None/Presentation/Cinema/Bright/Movie/Photos/ISF(Day/Night/Classroom)/User(1)/User2/ISF Day/Backboard/ISF Night/Classroom/3D/Game/Cinema			m1	-XX123 n	Oka	a=0/1/2/5/7/8/9/10/11	
	Power State		On/Off			m1	-XX124 n	Oka	a=1/0	
	Brightness					m1	-XX125 n	Oka		
	Contrast					m1	-XX126 n	Oka		

Appendices

-	X	X	X	X	X	n	CR	
Lead Code	Projector ID		Command ID			space	variable	carriage return
			4:3/16:9-1/16:9- #1:16:10/WindowLBXNative/AutoAuto235/Sup erWide4:3-II			n=1	-XX127 n	Ok a=1/2/3/5/6/7/10 for 4:3/16:9-1/16:9- #1:16:10/WindowLBXNative/A utoAuto4:3-II
		Aspect Ratio				n=1	-XX127 n	Ok
		Color Temperature	Warm Medium Cold			n=1	-XX128 n	Ok a=0/1/2 Warm/Medium/Cold
		Projection Mode	Front-Desktop Rear-Desktop Front-Ceiling Rear-Ceiling			n=1	-XX129 n	Ok a=0/1/2/3 for Front- Desktop/Rear-Desktop/ Front-Ceiling/Rear- Ceiling
		Output 3D State	n: 0/1 = 2D/3D				-XX503	Ok n0/1=2D/3D

Ceiling Mount Installation

1. To prevent damage to your projector, please use the Optoma ceiling mount.
2. If you wish to use a third party ceiling mount kit, please ensure the screws used to attach a mount to the projector meet the following specifications:

- ▶ Screw type: M3*3
- ▶ Maximum screw length: 10mm
- ▶ Minimum screw length: 7.5mm




❖ Please note that damage resulting from incorrect installation will void the warranty.



⚠ Warning:

1. If you buy a ceiling mount from another company, please be sure to use the correct screw size. Screw size will vary depending on the thickness of the mounting plate.
2. Be sure to keep at least 10 cm gap between the ceiling and the bottom of the projector.
3. Avoid installing the projector near a heat source.





Optoma Global Offices

For service or support please contact your local office.



USA

3178 Laurelview Ct.
Fremont, CA 94538, USA
www.optomausa.com

 888-289-6786
 510-897-8601
 services@optoma.com

Canada

2420 Meadowpine Blvd., Suite #105
Mississauga, ON, L5N 6S2, Canada
www.optoma.ca

 888-289-6786
 510-897-8601
 services@optoma.com


Europe

42 Caxton Way, The Watford Business Park
Watford, Hertfordshire,
WD18 8QZ, UK
www.optoma.eu
Service Tel : +44 (0)1923 691865

 +44 (0) 1923 691 800
 +44 (0) 1923 691 888
 service@tsc-europe.com


France

Bâtiment E
81-83 avenue Edouard Vaillant
92100 Boulogne Billancourt, France

 +33 1 41 46 12 20
 +33 1 41 46 94 35
 savoptoma@optoma.fr




Spain

C/ José Hierro,36 Of. 1C
28522 Rivas VaciaMadrid,
Spain

 +34 91 499 06 06
 +34 91 670 08 32




Deutschland

Wiesenstrasse 21 W
D40549 Düsseldorf,
Germany

 +49 (0) 211 506 6670
 +49 (0) 211 506 66799
 info@optoma.de

Scandinavia

Lerpeveien 25
3040 Drammen
Norway



 +47 32 98 89 90
 +47 32 98 89 99
 info@optoma.no

PO.BOX 9515
3038 Drammen
Norway

Appendices




Benelux BV

Randstad 22-123
1316 BW Almere
The Netherlands

 +31 (0) 36 820 0253
 +31 (0) 36 548 9052
www.optoma.nl



Latin America

3178 Laurelview Ct.
Fremont, CA 94538, USA
www.optomausa.com

 888-289-6786
 510-897-8601
 services@optoma.com


Korea

WOOMI TECH.CO.,LTD.
4F,Minu Bldg.33-14, Kangnam-Ku,
seoul,135-815, KOREA

 +82+2+34430004
 +82+2+34430005




Japan

東京都足立区綾瀬3-25-18
株式会社オーエスエム
サポートセンター:0120-46-5040

 info@osscreen.com
www.os-worldwide.com



Taiwan

5F., No. 108, Minchiuan Rd.
Shindian City,
Taipei Taiwan 231, R.O.C.
www.optoma.com.tw

 +886-2-2218-2360
 +886-2-2218-2313
 services@optoma.com.tw
asia.optoma.com



Hong Kong

Unit A, 27/F Dragon Centre,
79 Wing Hong Street,
Cheung Sha Wan,
Kowloon, Hong Kong

 +852-2396-8968
 +852-2370-1222
www.optoma.com.hk

China

5F, No. 1205, Kaixuan Rd.,
Changning District
Shanghai, 200052, China

 +86-21-62947376
 +86-21-62947375
www.optoma.com.cn

Regulation & Safety Notices

This appendix lists the general notices of your projector.

FCC notice

This device has been tested and found to comply with the limits for a Class B digital device pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This device generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this device does cause harmful interference to radio or television reception, which can be determined by turning the device off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the device and receiver.
- Connect the device into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/television technician for help.

Notice: Shielded cables

All connections to other computing devices must be made using shielded cables to maintain compliance with FCC regulations.

Caution

Changes or modifications not expressly approved by the manufacturer could void the user's authority, which is granted by the Federal Communications Commission, to operate this projector.

Appendices

Operation conditions

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference and
2. This device must accept any interference received, including interference that may cause undesired operation.

Notice: Canadian users

This Class B digital apparatus complies with Canadian ICES-003.

Remarque à l'intention des utilisateurs canadiens

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

Declaration of Conformity for EU countries

- EMC Directive 2004/108/EC (including amendments)
- Low Voltage Directive 2006/95/EC
- R & TTE Directive 1999/5/EC (if product has RF function)

Disposal instructions



Do not throw this electronic device into the trash when discarding. To minimize pollution and ensure utmost protection of the global environment, please recycle it.