PLC-XF41

XGA Digital Multimedia Projector



INCREDIBLY BRIGHT 7700 ANSI LUMENS

Utilizing four high-output 200 watt UHP lamps as its light source, the PLC-XF41 delivers an incredible 7700 ANSI lumens of brightness.

OUTSTANDING CONTRAST RATIO — 800:1

Through its new high-contrast optical system, the PLC-XF41 is able to achieve an outstanding contrast ratio of 800:1. A 10-bit digital gamma correction circuit is employed to effectively suppress overwhelming whites in bright images and excessive blacks in dark images.

SANYO s NEW PROGRESSIVE IC

A newly developed progressive integrated circuit provides highly improved playback of moving images. 1080 interlaced signals are converted into progressive signals while 2-3 pulldown doubles the resolution of images from DVD playback.

NETWORK CONTROL/ADMINISTRATION

An optional network board allows for simple control and management of the projector via a CAT5 network connection. The network board, which can memorize and store up to 55 PC modes, can also be used in parallel with RS-232 controllers.

REAL COLOR MANAGER

The Real Color Manager System provides white balance adjustment and gamma correction from a PC using the included image adjustment software by simply comparing the on-screen image to a printed color chart.

NEW ONE-TOUCH LENS REPLACEMENT

Attaching the included One-Touch lens mount adapters to your projector and lenses makes installation and removal of our optional lenses quick and easy.

SANYO PRESENTATION TECHNOLOGIES 21605 Plummer Street Chatsworth, CA 91311 Ph: 818.998.7322 ext. 288 Fax 818.717.2719 www.sanyolcd.com

PLC-XF41 Multi-Versatile Interface (POA-MD11DVI) (POA-MD16VD1) (POA-MD03VD2A) (POA-MD04VGA)



Specifications

Resolution	XGA (1024 x 768)					
Brightness	7700 ANSI Lumens (4-Lamp mode)					
Digitiless	3850 ANSI Lumens (2-Lamp mode)					
Uniformity	90% (corner to corner)					
LCD Panel System	1.8" TFT polysilicon type x 3					
Number of Pixels	2,359,296 (786,432 x 3)					
Contrast Ratio	800:1					
Projection Lens	Lens Sold Separately					
Image Size	Dependent on Lens					
Aspect Ratio	4:3					
Throw Distance	Dependent on Lens					
Zoom/Focus	Dependent on Lens					
Throw Ratio	Dependent on Lens					
Zoom Ratio	Dependent on Lens					
Power Lens Shift	Up/Down Ratio 10:0 – 0:10 or 8:1 – 1:8					
	Left/Right Ratio 3:2 – 2:3					
Digital Keystone	+ 40° / - 20°					
Correction						
Projection Lamp	200W UHP x 4					
Scanning Frequency	H Sync: 15-120kHz, V Sync: 50-120Hz					
Dot Clock Color System	230MHz DAL/DAL M/DAL N/SECAM/NTSC/NTSC/ 42					
Color System	PAL/PAL-M/PAL-N/SECAM/NTSC/NTSC4.43					
Computer Compatibility Voltage	UXGA, SXGA, XGA , SVGA, VGA, MAC 100-240V AC; 50/60/Hz (auto sense/select)					
BTU Rating	3924					
dB Rating	46.0					
Power Consumption	1150W					
Dimensions (WxHxD)	22.9"x9.9"x30.8"					
Net Weight	81.6 lbs.					
User Maintenance	Clean air filters, replace lamp assembly					
Detachable Input Panels	crean an mers, replace hanp assembly					
POA-MD11DVI	Digital Visual Interface (DVI-I) • Left & Right Audio					
	(RCA x 2) • Control (Min DIN 8-pin)					
POA-MD16VD1	RGB & Component (5-BNC) • Left & Right Audio					
	(RCA x 2) • Control (Min DIN 8-pin)					
POA-	Composite & Y/C (2-BNC) • S-Video					
MD03VD2A	• Left & Right Audio (RCA x 2)					
POA-	VGA (D-Sub 15) • Left & Right Audio (RCA x 2)					
MD04VGA	• Control (Min DIN 8-pin)					
Fixed Input/Output Panel						
Third input output Funct	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2)					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini);					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini);					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block					
	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA					
	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & 					
	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • 					
Included Accessories	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual 					
	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HID - HD-SDI Input Panel 					
Included Accessories	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual 					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD09VD3 – Faroudja TM Input Panel POA-MD13NET – Network Board POA-MD15SDI - SD-SDI Board					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD09VD3 – Faroudja TM Input Panel POA-MD15SDI - Network Board POA-MD15SDI - SD-SDI Board POA-LNA02 - Lens Mount Adapter					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD08HD - HD-SDI Input Panel POA-MD15NET – Network Board POA-MD15NET – Network Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD08HD - HD-SDI Input Panel POA-MD13NET – Network Board POA-MD15SDI - SD-SDI Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01 lenses)					
Included Accessories	Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD08HD - HD-SDI Input Panel POA-MD13NET – Network Board POA-MD13NET – Network Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01 lenses) POA-LNA01 - Lens Mount Adapter (for all other					
Included Accessories	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD09VD3 – Faroudja™ Input Panel POA-MD13NET – Network Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01 lenses) POA-LNA01 - Lens Mount Adapter (for all other lenses) 					
Included Accessories Optional Accessories	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD • HD-SDI Input Panel POA-MD09VD3 – Faroudja™ Input Panel POA-MD13NET – Network Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01 lenses) POA-LNA01 - Lens Mount Adapter (for all other lenses) PLCCSE14 - Hard Shipping Case 					
Included Accessories	 Serial in/out (D-Sub 9 x 2) • Audio out (RCA x 2) • USB (type B) • Wired RC jack (Stereo mini); Wired/Wireless I/R Remote Control w/Mouse Pad and Laser Pointer • 2 "AA" Batteries • AC power cord • VGA and DVI Cables • Wired remote cable • PS/2, Serial, MAC Control cables • Light Block Sheets • Dust cover • MAC/VGA and DVI/VGA Adapters • Lens Mount Adapters (POA-LNA02 & POA-LNA01) • Real Color Manager CD-ROM • Owner's manual POA-MD08HD - HD-SDI Input Panel POA-MD09VD3 – Faroudja™ Input Panel POA-MD13NET – Network Board POA-LNA02 - Lens Mount Adapter (for LNS-W02, W02KS, M01, S01 lenses) POA-LNA01 - Lens Mount Adapter (for all other lenses) 					

Because its products are subject to continuous improvement, SANYO reserves the right to modify product design and specifications without notice and without incurring any obligations.

Lens Specifications										
			On-Axis	Standard	Standard	Standard	Semi-Long			
Туре	Short Fixed	Short Zoom	Short Fixed	Zoom 1	Zoom 2	Zoom 3	Zoom	Long Fixed	Long Zoom	
Part No.	LNS-W01	LNS-W02	LNS-W03	LNS-S01	LNS-S02	LNS-S03	LNS-M01	LNS-T01	LNS-T02	
Zoom	No	Yes (power)	No	Yes (power)	Yes (power)	Yes (power)	Yes (power)	NO	Yes (power)	
Throw Ratio	1.2:1	1.35 — 1.8:1	0.8:1	1.8 — 2.9:1	2.0 — 2.6:1	2.6 — 3.5:1	3.5 — 4.6:1	7.0:1	4.6 — 6.0:1	
F Stop	2.5	2.5 — 2.9	2.6	2.6 — 3.5	2.0 — 2.3	1.7 — 2.6	2.0 - 2.6	2.0	2.0 — 2.9	
Length	9.4	8.34	9.25	7.0	8.2	13.8	6.9	8.6	9.6	



7700	ANSI	LUMENS	• TRU	E XGA	• DIGIT	AL MUL	TIMEDIA	PROJ	ECTOR
Weight	12.8 lbs.	5.5 lbs.	6.6 lbs	3.7 lbs.	4.2 lbs.	8.2 lbs.	4.2 lbs.	8.4 lbs.	6.8 lbs.