
Specification

			M420X	M420XV	
LCD Panel	D Panel 0.63 inch LCD with Micro Lens Array (Aspect Ratio 4:3)				
			Dichroic mirror separation-prism convergence system		
Resolution*1				68 pixels	
Lens		Manual Zoom / Manual Focus, Zoom ratio 1 to 1.7, Throw ratio 1.3 to 2.2, F1.7-2.1, f=17.5-29.0mm			
Lamp			265W AC(195W in ECO1)		
	co Mode On / Eco		3500H / 3000H		
	ojection Distance	e)	25 to 300 inch (0.64m to 13.77m)		
Colour Reprod		E 11 1 0/	10-bit signal processing (1.07 billion colours) (VIEWER, NETWORK : 16.7 million colours)		
Light Output*3 *4 Eco Mode Off			4200 ANSI lumens		
Eco Mode On		Eco Mode On	Approx.75% of Eco Mode Off 2000:1		
Contrast Ratio (White / Black)*4 Maximum Resolution Analog		Analog	UXGA (1600 x 1200) with Advanced AccuBlend		
<u></u>		Digital	HDTV (1920 x 1080) with Advanced AccuBlend		
Scan Rate Ho		Horizontal	15kHz to 100kHz (RGB : 24kHz or over)		
		Vertical			
		Vertical	50Hz to 120Hz (HDMI : 50Hz to 85Hz) Auto / Manual Approx.±Max 30 degrees		
Input	2 Computer	2 D-Sub Mini 15pin	VGA, SVGA, XGA, XGA+, WXGA, WXGA+, SXGA, SXGA+, UXGA		
Terminals	Input			Sync : 4.0Vp-p/TTL Level	
	nput	2 Stereo Mini Jack	Stereo L/R 0.5Vrms/22kΩ or over	-	
	2 Component	2 D-Sub Mini 15pin		Cb, Cr (Pb, Pr) : 0.7Vp-p/75Ω	
	Input	(Shared with	Compatible signals : 480i, 480p, 720p, 1080i, 1080p /60Hz, 576i, 576p, 720p, 1080i/50Hz		
	niput	Computer IN)		sive (50/60Hz)	
		Audio Input is Shared			
		with Computer IN	Same as Computer IN	-	
	1 HDMI Input	1 HDMI Type A	VGA, SVGA, XGA, WXGA, SXGA	/ 480p, 576p, 720p, 1080i, 1080p	
				. Specification, with H.D.C.P.	
		HDMI support audio	Audio format : LPCM Number of channel : 2ch		
			Sampling Frequency : 32/44.1/48kHz Sampling bit : 16/20/24-bit		
	1 S-Video	1 Mini DIN-4pin	Y : 1.0Vp-p/75Ω C : 0.286Vp-p/75Ω		
	Input	1 RCA pin x 2	tereo L (MONO)/R : 0.5Vrms/22kΩ or over -		
	1 Video Input	1 RCA pin	Compatible signals : NTSC/NTSC4.4	3/PAL/PAL-N/PAL-M/PAL-60/SECAM	
			Compatible Video : 1.0Vp-p/75Ω		
		Audio Input is			
		Shared with S-Video	Same as S-Video	-	
Output	1 RGB Output	1 D-Sub Mini 15pin	Only Computer 1 in	nput can be output	
Terminals	1 Audio Output	1 Stereo Mini Jack	Stereo L/R 0.5Vrms/22kΩ or over,		
			Selected Audio Signal input can be output	-	
USB Port		1 Type A	USB2.0 (for US	B memory)	
1 Type B		1 Type B	USB2.0 (for PC)		
Wired LAN Por		1 RJ-45		100BASE-TX	
Wireless LAN (1 Type A	IEEE 802.11 b/g/n (Optional US		
Control Terminal		1 D-sub 9Pin	RS-2	32C	
Built-In Speake			10W Monaural	-	
	Mode On / Eco			/ 36dB	
Environment	Operational Temperatures		5°C to 40°C ([ECO MODE] selected automatically at 35°C to 40°C),		
			20% to 80% Humidity (Non-Condensing)		
	Storage Temperatures		-10°C to 50°C, 20% to 80% Humidity (Non-Condensing)		
Power Require	ment			C, 50Hz/60Hz	
Input Current				- 1.7A	
Power	Eco Mode Off	100 - 130V	358W		
Consumption	Faat Mada	200 - 240V	343W		
	Eco1 Mode	100 - 130V	271W		
	Oterally 14	200 - 240V	264W		
	Standby Mode	100 - 130V / 200 -240V	8W		
	Power-saving	100 - 130V	0.2W		
	Mode	200 - 240V	0.4W		
Calorific Value		100 - 130V	1222BTU (Max)		
200 - 240V Dimensions (W x H x D)			1170BTU (Max) 398mm x 115mm x 282mm (Not Including Protrusions)		
Dimensions (W Weight	x n x D)		398mm x 115mm x 282mm 3.6kg	(Not Including Protrusions) 3.5kg	
Accessories			З.ькд Remote control, Batteries(AAA x 2), Computer		
Accessories				nportant information	
Regulations	For United States				
neguiations		For Canada	UL Approved (UL 60950-1), Meets FCC Class B Requirements		
		For Asia/Oceania	C-UL Approved (CSA 60950-1), Meets DOC Canada Class B Requirements IEC60950-1, Meets AS/NZS CISPR.22 Class B		
		For Korea	KC (safety : K60950-1, EMC : K00022, K00024, K61000-3-2)		
		For China	GB4943, GB9254, GB17625.1		
		For Russia			
			Gost R 60950-1, 51318.22, 51317.3.2./3.3.		


Throw Distance and Screen Size



A420X/M420XV (Aspect ratio 4:3)

Screen size (inch)	Throwing distance(m)		Bottom height			
Screen size (inch)	Wide	Tele	(cm)			
25 (0.51x0.38)	0.64	1.09	6.0			
30 (0.61x0.46)	0.78	1.32	7.1			
40 (0.81x0.61)	1.05	1.79	9.5			
60 (1.22x0.91)	1.61	2.71	14.3			
80 (1.63x1.22)	2.17	3.63	19.1			
100 (2.03x1.52)	2.72	4.55	23.8			
120 (2.44x1.83)	3.28	5.47	28.6			
150 (3.05x2.29)	4.11	6.86	35.7			
180 (3.66x2.74)	4.95	8.24	42.9			
200 (4.06x3.05)	5.50	9.16	47.6			
240 (4.88x3.66)	6.61	11.01	57.2			
300 (6.10x4.57)	8.28	13.77	71.4			
*The values in the tables are design values and may vary						

Cabinet Dimensions



*1 : Effective pixels are more than 99.99%

12: Energies defined as the average time span for the brightness of the lamp to be reduced by half, it dose not refer to the warranty period for the lamp.
 2: Lamp life is defined as the average time span for the brightness of the lamp to be reduced by half, it dose not refer to the warranty period for the lamp.
 3: This is the light output value (ANS) lumens) when the [PRESET] mode is set to [HIGH-BRIGHT].
 If any other mode is selected as the [PRESET] mode, the light output value may drop slightly.
 4: Compliance with ISO21118-2005

All specifications are subject to change without notice



The projector can be unplugged during its cool down period after it is turned off.
 Parts of the projector will become heated during operation. Use caution when picking up the projector immediately after it has been operating.
 Use caution when putting the projector in the soft case immediately after the projector has been operating. The projector cabinet is hot.

 Virtual Remote Tool uses WinI2C/DDC library. @Nicomsoft Ltd. HDMI, the HDMI Logo and High-Definition Mutually encontrast Eta.
 HDMI, the HDMI Logo and High-Definition Mutually encontrast Eta.

In HUWI Learning LEC. In the registered trademark of the Wi-Fi Alliance. rademark PJLink is a trademark applied for trademark rights in Japan, the United States of America and other countries and areas.

All other trademarks are the property of their respective owner The images in this brochure are samples

This brochure uses recycled paper



High-brightness projector

M420X/M420XV





Cat.No. WLPJ-1102-331NN

Empowered by Innovation





wide range of applications.

http://www.nec-display.com/ap/

From classrooms to boardrooms, these high-bright, multi-function projectors adapt seamlessly to a wide range of spaces.

Features designed to make installation and maintenance easy

A convenient test pattern for picture adjustment


You can check the screen projection condition while setting up the projector by using a test pattern (grid). The projector can be checked independently without having to connect image devices and output test images



.....

A geometric correction function to enable projection to a screen on an angle

The Geometric Correction Tool (GCT) of included Image Express Utility Lite software enables the projection of images from a computer to screen on an angle and to screens with complex shapes.



An optional cable cover is available

The optional cable cover (NP01CV) can hide cables even in situations where cables standout, such as with ceiling mountings. With the cable cover attached to the projecto



Equipped with a large, maintenance-free filter

The large filter has the two-layer construction. It provides excellent dust protection and eliminates the need for regular cleaning. Just replace the filter when you change the lamp.



The 1.7x zoom provides excellent flexibility for installation locations

The projector supports a 1.7x zoom to cover a wide throw distance.

Advanced functionality designed for ease of operation

A USB display function for simple connection with a single USB cable

The USB display function lets you connect the projector and a computer with a standard USB cable to easily project computer screen images without computer cables.



"No-signal guidance" for easy cable connections

When there is no signal being input, the "No-signal guidance" display appears on the screen. Since you know in a glance where the cable should be inserted, your setup runs smoothly



A guidance to tell no signal input

Supports Virtual Remote Tool for operation of projectors from a computer

*Use the included Virtual Remote Tool software

Images can be sent over a LAN using the wired/wireless LAN option* *Use the included Image Express Utility Lite software



*Model name of the optional wireless LAN unit varies depending on the country where the unit is used (or to be used) NP02LM1 : United States, Canada, Mexico, Taiwan, Brazil, Colombia

VP02LM2 : Europe, United Arab Emirates, Saudi Arabia, Oman, South Africa, Turkey, Ukraine, Egypt, Israel, Australia, New Zealand, Japan, Thailand, China, Hong Kong, Singapore, South Korea, Malavsi ri Lanka, Pakistan, Vietnam, India, Indonesia, Philippines, Peru, Chile, Argentina, Ecuador NP02LM3 : Bussia

Auto Vertical Keystone Correction

- Wall Colour Correction for vivid images even without a screen
- Front ventilation for effective heat dissipation




Added functions for the economical use of energy and the reduction of total cost of ownership

Equipped with an automatic Eco Mode to automatically control picture brightness

Eco Mode reduces light intensity automatically and imperceptibly when switching from white

screens like charts or bright images to a dark screen or image. This function can reduce the power consumption by up to 24%. Both the projector and its remote are equipped with an Eco button for easy setting of Eco Mode.



Equipped with an abundance of handy functionality

Light

High brightness up to 4200 ANSI lumens

*Not available on M420XV

directly into the projector.

*Supported graphic format is JPEG.

Built-in monaural speaker

with a powerful 10 W output

Computer-free presentations

The projector allows you to project images

without a computer. Simply insert a USB

memory device loaded with image data

Basic DICOM mode allows simple display of medical images

The projector is preset with gradation characteristics for medical images (similar to DICOM standards). You can display medical images stored as DICOM files for presentations at academic conferences, etc.

*Cannot be used for the display of images for medical diagnosi

The Quick start function starts projection a mere 3 seconds after the power is switched on





Using Eco Mode can increase the lamp lifetime to 3500 hours*. Furthermore, the low-energy design keeps power consumption to 0.2 W during standby (low energy consumption), which helps reduce total cost of ownership. *This is not a guaranteed value.

Lengthen lamp lifetime

The Carbon Meter lets you visually check the amount CO2 you reduced



Quick Cooling and Direct Power Off allow speedy clean-up and transfer after use

Designed for a low noise level of 30dB (in Eco Mode) that doesn't disturb conferences or lessons

The RPM of the fan has been reduced and operation noises have been suppressed for a substantial reduction in noise.

The security function uses password settings and key locks to prevent unauthorized use