

# BenQ DLP™ Projector

 PB8260



## Key Feature:

- DLP™ projection system
- XGA native resolution
- 3500 ANSI Lumens
- Wireless Presenter (802.11b)
- Extension Mode
- Brightest DLP™ projector with Wireless Function
- 2000:1 contrast ratio
- Micro Dust Filters
- T-flow Air Cooling System
- 8 sets of Preset Modes
- Versatile Connectivity
- 3000 hrs Lamp Life
- HDTV Compatible



The DLP™ logo and DLP™ medallion are trademarks of Texas Instruments®.

## Specifications

Projector system	DLP™ technology by Texas Instruments®
Native Resolution	XGA (1024 x 768)
Resolution Supported	640 x 350 to 1280 x 1024
Brightness	3500 ANSI lumens (80% at economic mode)
Contrast Ratio	2000:1
Aspect Ratio	Native 4:3, 16:9 Selectable
Color	Full 16.7 million color palette
Lens	F = 2.4 to 2.6, f = 24.0 to 29.1 mm
Zoom Ratio	Manual zoom, 1.22:1
Image Size (Diagonal)	22" to 300"
Throw Ratio	60" @ 6.6 feet (60" @ 2m)
Lamp	300W, 2000/3000 hours (Normal/Economic mode)
HDTV Compatibility	480p, 576p, 720p, 1080i
Video Compatibility	NTSC, PAL, SECAM
Horizontal Frequency	24 ~ 88 kHz
Vertical Scan Rate	48 ~ 100 Hz
Input Terminal	PC <ul style="list-style-type: none"> <li>Analog RGB: D-sub 15 pin x 1 (shared)</li> <li>Analog RGB: DVI-I x 1 (shared)</li> <li>Digital RGB: DVI-I x 1</li> <li>Wireless Network**</li> </ul>
	A/V <ul style="list-style-type: none"> <li>Component Video: D-sub 15 pin x 1 (shared)</li> <li>S-Video: Mini DIN 4 pin x 1</li> <li>Composite Video: RCA x 1</li> </ul>
	Audio <ul style="list-style-type: none"> <li>Video L/R audio: Audio L/R RCA x 2</li> </ul>
Output Terminal	Analog RGB: D-sub 15 pin x 1 2 Watt Speaker x 2
Control Terminal	Mouse Control: USB x 1 (shared) RS-232 Serial Control: Mini Din 9 pin x 1 USB Serial Control: USB x 1 (shared)
Dimension (W x H x D in)	12.6 x 4.2 x 9.3 (320 x 106 x 236 mm)
Weight	8.4 lbs (3.8 kg)
Power Supply	100 to 240 VAC, 50 to 60 Hz
Power Consumption	410 W (Max., 80% at Economic mode)
Audible Noise	<34/31 dB (Normal/Economic mode)
On-Screen Display Languages	English/French/German/Italian/Spanish/Korean/Simplified Chinese/Traditional Chinese/Japanese/Russian
Preset Modes	PC Input: <ul style="list-style-type: none"> <li>Presentation Mode</li> <li>Video Mode</li> <li>Vivid Mode</li> <li>Economic Mode</li> </ul>
	A/V Input: <ul style="list-style-type: none"> <li>Gaming Mode</li> <li>Video Mode</li> <li>Cinema Mode</li> <li>Economic Mode</li> </ul>
Features	Digital Keystone Auto Adjustment Freeze Blank Progressive Scan Digital Zoom Source Detection
	Laser Pointer HDTV Compatible Preset Modes PIP (picture in picture) Mute Wireless Function Extension Mode
Accessories (Standard)	User's Manual Quick State Guide Manual CD Software CD Wireless Card Warranty Information Booklet Remote Control AAA Batteries
	Soft Carrying Case VGA Cable VGA-Component Cable VGA-DVI-I Cable PC Audio Cable L/R Audio Adapter USB Cable PWR Cord
Accessories (Optional)	Ceiling Mounting Kit Mac Adapter Lamp Module
	3-2 Adapter Presentation Pro Micro Dust Filter

\*\*Support XGA input resolution only

**BenQ**

Enjoyment Matters

**ProSelecta**

View :: Compare :: Select - [www.ProSelecta.com](http://www.ProSelecta.com)